



# MEA2100-PE2x60 and MEA2100-HE2x60 **Perfusion Element and Heating Element Rev B**

Instructions for the Replacement of the Perfusion Element and / or Heating Element of the Headstage MEA2100-HS2x60 of the MEA2100-System.

**Important:** Disconnect the MEA2100-System from the electrical outlet!

Please follow the instructions with great care. Only experienced persons should change the elements on the ground plate of the MEA2100 headstage.



Perfusion Element Heating Element

## MEA2100-HS2x60-System

Ground plate of the headstage equipped with heating element **MEA2100-HE2x60** and perfusion element MEA2100-PE2x60.

Turn the ground plate of the MEA2100 headstage around and put it onto a soft surface to avoid scratches. You need a TORX T6 screw driver to remove the designated screws (M2 x 4). Unscrew the ten screws which fix the cover for the tubing and the platine of the heating element. Keep the screws for reusing them later.



Remove the two screws (M2  $\times$  3) which fix the steel tubes of the perfusion element. These two screws are shorter than all other screws. Do not mistake the screws!





Multi Channel Systems MCS GmbH Aspenhaustrasse 21 72770 Reutlingen Germany

Phone +49-7121-909 25-0 +49-7121-909 25-11 Fax

sales@multichannelsystems.com www.multichannelsystems.com

© 2019 Multi Channel Systems MCS GmbH a division of Harvard Bioscience, Inc.

June 2019

Product information is subject to change without notice



# MEA2100-PE2x60 and MEA2100-HE2x60 Perfusion Element and Heating Element **Rev B**

Instructions for Replacement

Important: Disconnect the MEA2100-System

from the electrical outlet!

Outlet Inlet MEA2100-PE2x60 Perfusion Element, Rev B







Metal plate for shielding

the ground of the headstage. Please use a TORX T6 screw driver. Unscrew the 8 screws (M2 x 4) to remove the metal plate and the perfusion element.

**Replacement of a Perfusion Element** 



## MEA2100-HE2x60 Heating Element, Rev B



## **Replacement of a Heating Element**

Unscrew the 12 screws (M2 x 4) which fix the heating element in the ground plate. Remove the heating element together with the printed circuit board and the connector, if you want to replace the heating element with a perfusion element.

Remove only the heating element to replace it with another heating element. Connect the replacement to the connector of the printed circuit board.



Multi Channel Systems MCS GmbH Aspenhaustrasse 21 72770 Reutlingen Germany

Phone +49-7121-909 25-0 +49-7121-909 25-11 Fax

sales@multichannelsystems.com www.multichannelsystems.com

© 2019 Multi Channel Systems MCS GmbH a division of Harvard Bioscience, Inc.

June 2019

Product information is subject to change without notice.